



E-ECU 2

| | | |
|----------|--------|------|
| INJ-1L | CN2-1 | 125D |
| INJ-2L | CN2-2 | 125B |
| MPROSP-H | CN2-4 | 125P |
| HPSOL | CN2-5 | 0.5R |
| SVS | CN2-8 | 0.5R |
| TEO | CN2-11 | 0.5L |
| PDPFH | CN2-12 | 0.5G |
| INJ-1L | CN2-16 | 125R |
| INJ-2L | CN2-17 | 125L |
| INJ-3L | CN2-18 | 125Y |
| IVDCM-H | CN2-19 | 125L |
| IVDCM-L | CN2-20 | 0.5B |
| A_GND | CN2-25 | 0.5G |
| PRAIL | CN2-26 | 0.5G |
| TV | CN2-28 | 0.5G |
| A_GND | CN2-29 | 0.5L |
| UBS | CN2-30 | |
| INJ-1H | CN2-31 | 125Y |
| INJ-2H | CN2-32 | 125G |
| INJ-1H | CN2-33 | 125L |
| REOP1 | CN2-34 | 0.5L |
| CMSPD | CN2-37 | 0.5B |
| A_GND | CN2-38 | 0.5W |
| CKSPD | CN2-39 | 125W |
| INJ-2H | CN2-47 | |
| INJ-3H | CN2-48 | |
| A_GND | CN2-51 | 0.5B |
| A_GND | CN2-52 | 0.5B |
| CKSPD | CN2-54 | 0.5B |
| TIAR | CN2-59 | 0.5L |
| UB2 | CN2-60 | 125R |

E-ECU 1

| | | |
|--------------|--------|-------|
| VB | CN1-1 | 2.0W |
| GND | CN1-2 | 2.0B |
| VB | CN1-3 | 2.0W |
| GND | CN1-4 | 2.0W |
| VB | CN1-5 | 2.0W |
| GND | CN1-6 | 2.0B |
| APP-IP6 | CN1-13 | 0.5W |
| APP-IP9 | CN1-14 | 0.5B |
| LOPSW | CN1-15 | 0.5B |
| APP-IP4 | CN1-16 | |
| APP-IP8 | CN1-17 | 0.5L |
| REGSW | CN1-18 | |
| APP-IP3 | CN1-19 | 0.5G |
| IVPS | CN1-20 | 0.5B |
| A_GND | CN1-21 | |
| POLSW | CN1-22 | 0.5R |
| SVS | CN1-23 | 0.5R |
| SVS | CN1-24 | 0.5B |
| DPF-M1 | CN1-25 | 0.5WG |
| APP-OP2 | CN1-26 | 0.5W |
| DPF-M2 | CN1-27 | 0.5P |
| STR-RLYD-UB5 | CN1-28 | |
| UB2 | CN1-29 | |
| REGMSW | CN1-31 | |
| SHUDNSW | CN1-32 | 0.5R |
| TEGR | CN1-33 | 0.5G |
| STARTSW | CN1-35 | |
| REGAN | CN1-36 | |
| APP-IP1 | CN1-37 | |
| APP-IP2 | CN1-38 | 0.5W |
| PEGR1 | CN1-39 | |
| WSSW | CN1-40 | |
| ACLSW | CN1-41 | |
| APP-IP5 | CN1-42 | 0.5R |
| SVS | CN1-43 | |
| SVS | CN1-44 | 0.5R |
| SVS | CN1-45 | |
| SVS | CN1-46 | |
| LOAD-MID UB2 | CN1-47 | |
| REOP1 | CN1-48 | |
| OVHT-LMP | CN1-49 | 0.5R |
| PREHT-LMP | CN1-50 | 0.5L |
| UB3 | CN1-51 | 125R |
| A_GND | CN1-52 | 0.5B |
| CAN2L | CN1-53 | 0.5L |
| CAN2H | CN1-54 | 0.5P |
| A_GND | CN1-55 | 0.5Y |
| TEXMH | CN1-56 | |
| APS3 | CN1-58 | |
| A_GND | CN1-60 | 0.5P |
| APS1 | CN1-61 | 0.5B |
| A_GND | CN1-62 | 0.5L |
| PDPF | CN1-63 | 0.5L |
| D_GND | CN1-65 | 0.5B |
| CHGSW | CN1-66 | 0.5R |
| APP-IP7 | CN1-67 | 0.5G |
| UB2 | CN1-68 | 0.5L |
| UB2 | CN1-69 | 0.5W |
| SAID-RLY | CN1-70 | 0.5G |
| DPF-M4 | CN1-71 | |
| REOP3 | CN1-72 | 125G |
| UB3 | CN1-73 | 0.5B |
| A_GND | CN1-74 | 0.5Y |
| CAN2H | CN1-75 | 0.5L |
| CAN2L | CN1-76 | 0.5L |
| A_GND | CN1-77 | 0.5B |
| TEAIR | CN1-79 | 0.5P |
| TOPFM | CN1-80 | 0.5B |
| TOPFI | CN1-81 | 0.5R |
| APS2 | CN1-83 | |
| A_GND | CN1-84 | 0.5Y |
| PEGR | CN1-85 | 0.5D |
| WDSBWS | CN1-86 | |
| D_GND | CN1-87 | 0.5Y |
| IGNSW | CN1-88 | |
| UB3 | CN1-89 | 0.5D |
| UB3 | CN1-90 | 0.5D |
| FAIL-LMP | CN1-92 | 0.5R |
| APP-OP1 | CN1-93 | |
| NRPM-MID UB3 | CN1-94 | |

Wiring Color List

| | | | | |
|------------|----------|----------|----------|----------|
| W:White | G:Green | V:Violet | R:Red | Y:Yellow |
| Sb:SkyBlue | P:Pink | L:Blue | O:Orange | B:Black |
| Gy:Gray | Br:Brown | | | |

