



Wiring Color List
 W:White G:Green V:Violet R:Red Y:Yellow
 Sb:SkyBlue P:Pink L:Blue O:Orange B:Black
 Gy:Gray Br:Brown

ECU
 D06(IP01) CN1-1 0.5R
 AVSS CN1-2 0.5BR
 AVCC CN1-3 0.5BR
 TXD CN1-4 0.5BY
 D03(IP30) CN1-5 0.5WR
 D03(IP30) CN1-6 1.25B
 CAN-H CN1-8 0.5Y
 CAN-L CN1-9 0.5G
 D04(IP31) CN1-10 0.5OB
 RXD CN1-11 0.5Y
 D02(IP21) CN1-12 0.5Y
 GND CN1-13 0.5B
 CAN-L CN1-14 0.85LB
 AN3 CN1-15 0.85W
 START_ENA CN1-16 0.5W
 LR CN1-17 1.25YR
 ON CN1-18 0.55B
 D07(IP1) CN1-21 0.5V
 AN2 CN1-22 0.5V
 AN0 CN1-23 0.5W0
 ENG_STOP CN1-24 0.5YW
 D00(PROG(P43)) CN1-25 1.25YR
 CN1-26

D08(IPA1) CN2-1 0.5LY
 D09(IPA2) CN2-2 0.5RG
 D10(IPA3) CN2-3 0.5BR
 D11(IPA4) CN2-4 0.5BR
 D12(IPA5) CN2-5 0.5RY
 D13(IP7A) CN2-6 0.5LR
 D14(IP7I) CN2-7 0.5Y
 P.WM4 CN2-8 0.85LB
 P.WM5 CN2-9 1.5WR
 D19(IP96) CN2-10 0.5RL
 D10(IP65) CN2-11 0.5W
 D14(IP53) CN2-12 0.5Y
 D14(IP53) CN2-13 0.5OB
 D10(IP70) CN2-14 0.5WR
 D15(IP70) CN2-15 0.5WR
 D15(IP70) CN2-16 0.5YL
 P.WM1 CN2-17 1.25YG
 D17(S1) CN2-18 0.5G
 RIGHT(IP82) CN2-19 0.5BG
 D18(IP82) CN2-20 0.5W
 DOWN(IP62) CN2-21 0.5O
 D19(IP47) CN2-22 0.5YV
 D19(IP47) CN2-23 0.5LW
 D19(IP82) CN2-24 1.25YL
 D19(IP82) CN2-25 0.5L
 D19(IP82) CN2-26 0.5BY
 LEFT(IP80) CN2-27 0.5BR
 UP(IP64) CN2-28 0.5BY
 MGCL(IP93) CN2-29 0.85P
 D08(IP95) CN2-30 0.5GW
 P.WM3 CN2-31 0.85WR
 P.WM4 CN2-32 0.85GB
 P.WM4 CN2-33 1.255V
 P.WM2 CN2-34

Electromagnetic Clutch
 Surge Suppressor
 HST Motor
 Home Position
 Clutch Motor
 Actuation
 Chute Light
 Chute Guard Switch
 Working Light
 Chute Deflector Motor
 Chute Angle Motor

Surge Suppressor
 Alternator
 Starter Motor
 Battery